

3xLogic Vigil

01/10/2024 2:35 pm EST

Video Type: 3XLOGIC

Connection Type: IP

Access Type: Direct connect to device (URL)

Notable Features, Limitations and Recommended Usage:

Typical Configuration: Unit at site accessible via IP by the Central Station.

Live Connection: Live connections can be made from a Device the Device itself or on a Floor Plan.

Software: The 3xLogic SDK needs to be installed separately from the VCC install. The DirectX June 2010 redistributable might be needed on a machine by machine basis.

SDK Version: VigilSDK 9.50.0.406

Available Options:

- Live Video
- Metadata
 - Device name
- PTZ (if supported by camera)
 - Direct control
 - Presets
 - Tours
 - Relay Output
- Live Audio (if supported by camera)
 - Listen
 - Audio Talk-down (if supported by camera)
- Recorded Playback
- Image Snapshot (to file, clipboard, or history)
- Video Clip Export (to file or history)

Device Address Syntax:

IP Address: ###.###.###.###

or

Resolvable DNS Name: server.somewhere.com

Device Option Syntax:

<parameter>=<value>&<parameter>=<value> ...

Available User Options:

<parameter>= <value>	Acceptable Values	Description
camera=<int>	Single integer starting from 0	Camera number for this device. Required
user=<string>	Any string	The username that has permission to view live video on this device. Required
password=<string>	Any string	NVR password. Required
port=<int>	Integer	Network port to connect to the 3xLogic device Required
vigilcon=<int or bool>	0, 1, true, false	Whether to use the 3xLogic Vigil Connect service to connect to the device. Optional (default false)