

# Digital Watchdog

01/10/2024 2:43 pm EST

**Video Type:** DIGWDOG

**Connection Type:** Cloud

**Access Type:** Direct connect to NVR via Proxy

**Notable Features, Limitations and Recommended Usage:**

**Typical Configuration:** Unit at site accessible via Cloud by the Central Station.

**Live Connection:** Live connections can be made from a Device the Device itself or on a Floor Plan.

**Software:** None

**SDK Version:** None

**Discoverable:** Selecting the Discover icon in the Devices screen of the Manitou Web Client, the user can choose to create a container or just the individual devices. They will enter in the User, Password, and Options then click Discover to find all devices available. The user can select to pull in all the devices or some, rename the devices, and have it automatically create the reference screenshot for video devices. The User and Password will then be added encrypted to each individual device as well as the Options information.

User=<string>	Any string	User that connects to the NVR. <b>Required</b>
Password=<string>	Any string	Password for the user account that connects to the NVR. <b>Required</b>
Options=<string>	Any string	See below under Available User Options. <b>Required</b>

**Available Options:**

- Live Video
- Metadata
  - Device name
- PTZ (if supported by camera)
  - Direct control
  - Presets
  - Relay Output

- Live Audio (if supported by camera) FUTURE FUNCTIONALITY
  - Listen
  - Audio Talk-down (if supported by camera)
- Recorded Playback
- Image Snapshot (to file, clipboard, or history)
- Video Clip Export (to file or history)

**Device Option Syntax:**

<parameter>=<value>&<parameter>=<value> ...

**Available User Options:**

<parameter>=<value>	Acceptable Values	Description
cloudname=<string>	Any String	Cloud address where the devices reside. <b>Required</b>
camera=<string>	Any string	Camera number and name for this device. <b>Required</b>