

Understanding Contact ID (Receiver Signals)

01/02/2024 2:07 pm EST

Contact-ID

5RRLLs18AAAAQXYZGGCCC[DC4]

Where, 5 : Protocol number.

RR : Virtual Receiver number.

LLL : Virtual Line number.

s : Space.

18 : Contact-ID format identifier. (98 can also be used)

AAAA : Four digit account codes.

Q : Qualifier, E= New event or opening,

R= New restore or closing.

P= Previous event

XYZ : Class code and event codes.

GG : Group number.

CCC : Zone codes or user ID.

[DC4] : Terminator, 14 Hex.

Contact-ID (10 digit account) Protocol (Q)

QRRLLs58AAAAAAAAAAQXYZGGCCC[DC4]

Where, Q : Protocol number.

RR : Virtual Receiver number.

LLL : Virtual Line number.

s : Space.

58 : 10-digit account Contact-ID format identifier.

AAAAAAAAAA : Ten digit account codes.

Q : Qualifier, E= New event or opening,

R= New restore or closing.

P= Previous event

XYZ : Class code and event codes.

GG : Group number.

CCC : Zone codes or user ID.

[DC4] : Terminator, 14 Hex.* /